



HVAC Motor Doctor[®]
a distribution HVAC newsletter

August 2014

What the Motor Nameplate Doesn't Tell You

One of the most frequent challenges you may face as a service technician is determining if a replacement motor is suitable for an application. Often, you can use the motor's nameplate to help make the selection, but a nameplate doesn't always provide you with everything you need to know.

Take nameplate amps, for example. It is common practice to determine the power input of two motors by comparing nameplate amps of the original motor with those of the replacement. In other words, if the replacement motor's rated amps are at least as high as the original, you are reasonably safe in using it in the application. This practice works best when you're working with motor types whose efficiency varies little from one design to another. A good example would be three-phase motors.

But, the nameplate may not tell the entire story, and as a superior service technician, you need to be aware of what is missing. Motor nameplates typically do not include input watts as a power measurement, nor do they identify the motor's efficiency. In certain applications, this criteria may be critical factors in deciding if a replacement motor can do the job.

One case where the nameplate-amp comparison often breaks down is when you're working with single-phase motors. These motors which include permanent split capacitor motors, shaded pole motors, as well as split phase and capacitor-start versions, may vary widely in terms of efficiency within a single motor design. You have no way of knowing that, however, simply by looking at the nameplate.

So what happens to the nameplate amp comparison in this instance? Since nameplate amps reflect total current consumption of the motor (including current

converted to output power and current lost to heat), higher nameplate amps on a single-phase motor can just as likely indicate poorer conversion efficiency as increased power output. Faced with this challenge, the service technician dealing with single-phase motors needs to look beyond amps and compare the horsepower of the replacement motor to the original. If nameplate amps and horsepower compare favorably, you likely have a suitable replacement.

To be certain, it's important that you test the replacement motor in the application itself. This is especially true when you remember that there is not a single industry standard for motor efficiency. Best practice is to measure the amps through the motor terminal or power leads of the replacement and compare that reading with the amp rating shown on the replacement motor's nameplate. When you perform this test, make sure that the motor is in its normal operating state with all belts, blowers, baffles and enclosures in place. If you do not duplicate the motor's normal working environment, you will not get a true reading of the motor's total current consumption. It is possible to end up with an overloaded condition and eventually an unhappy customer.

Motor manufacturers are becoming increasingly sensitive to motor efficiency and are working to design motors that deliver higher power while consuming the same-or fewer-watts. All of this product development means that you, as a service technician, will probably see motors in the field of similar power output, but with significantly different ampacity. By being aware of these differences and understanding that you won't find this important information just by looking at the nameplate, you can provide correct replacements and better service to your customers.

How would you rate the value of this article?

lowest [1](#) [2](#) [3](#) [4](#) [5](#) [6](#) [7](#) [8](#) [9](#) [10](#) highest

Sorry, voting is closed.

Comfortech 2014

Attending Comfortech this year in Nashville, TN?
Make sure to stop by booth #829 to meet the team and check out real innovation, expertise and versatility.



When: September 9th - 11th

Where: Nashville Convention Center, booth #829


Upcoming ECM Training

Whether it's online training through webinars or onsite training throughout the country, our classes led by Training Manager, Christopher Mohalley, are a great way for anyone in the HVAC industry to learn more about ECM motors and ECM-equipped systems! Plus, NATE-certified technicians who participate receive 1 hour credit per each class hour taken toward recertification in all of their current forced-air disciplines. Visit theDealerToolbox.com for a complete schedule of upcoming [webinars](#) and [onsite trainings](#)!

EconoMaster - 3/4 HP 460V Now Available!

The EconoMaster, designed for residential and light commercial HVAC/R applications is now available in 3/4 HP 460V! The condenser fan replacement motor includes the following features:

- 70° C Ambient
- Class "F" Insulation
- Electrically Reversible
- Energy Efficient
- Single Phase
- Auto Protector
- 26" Lead Length
- UL/CSA Approved



The stock number for the 3/4 HP 460V EconoMaster is **EM3739F**. For more information on this motor or the EconoMaster line, contact your Regal Sales Professional or Customer Service today at (800) 672-6495 or check out our [EconoMaster Bulletin!](#)