



HVAC Motor Doctor[®]
a distribution HVAC newsletter

September 2014

Reducing Motor Noise

Dealing with a user's complaint of a noisy motor can be a frustrating experience. After all, the perception of noise is extremely subjective. Not only does the range of human hearing differ considerably among people, but it also varies by specific frequency.

Another frustration is that noise is not an easy condition to measure. Part of that difficulty goes back to the subjective perception of noise. A more technical reason is that noise is the perceived result of a complex interaction of sound waves. Measuring noise can be like measuring chaos.

All noise has a mechanical origin, which is to say it is the result of waves of pressure transmitted through air as the result of the mechanical movement of some object. In a motor, the sources of mechanical noise are numerous:

So-called "electrical noise" is the result of mechanical pressure produced when the parts of a motor that can be magnetized are attracted and repelled from one another. This happens when the magnetic field that drives the motor alternates.

Another source of noise is inherent in a motor's relationship to both the mechanical and electrical effects of spinning parts moving through the air gap.

Additionally, since the motor has a spinning internal part (namely, the rotor) imbalances are transferred to the frame of the motor as noise.

Noise inherent in a motor generally cannot be "cured" by the motor installer. But short of specifying a low-noise motor for the application, there are several things the savvy installer can do to minimize the effects of inherent motor noise.

The first course of action is fairly straightforward— isolation. Inherent noise is very efficiently transferred to the motor's frame through its mechanical parts. Isolation breaks that efficient path to the motor-driven device. You can isolate the motor in several ways, such as using rubber motor pads, soft couplings and/or resilient cradles.

There's a second course of action that you need to consider when the first step fails to produce the desired result. This is based on the concept of harmonics. Harmonics are a set of specific frequencies that noisy mechanical equipment tends to favor as vibration frequencies. Unfortunately, harmonic frequencies are not easy to calculate, as they are the result of complex interactions of speed, mass, and separation (or the distance between moving assemblies).

Though difficult to calculate, you can deal with the effect of harmonic frequencies effectively by changing the speed, mass, or separation distance of the motor-driven apparatus. For example, in a belt-driven application, pulley diameters could be changed to vary the speed of the driven load. Slight increases or decreases in speed from the unit's designed point could move the motor out of the harmonic frequency. Sometimes changing the density (hardness) of isolation devices, such as the rubber pads or resilient rings is enough to move a mechanical assembly off a harmonic frequency. Where space and application permit, changing the length of the train of driven equipment can also move that equipment off a

harmonic frequency.

Although subjective, motor noise is often the cause for call-backs by unhappy customers. Many times, you can solve the problem easily with isolation. But when the noise persists, a working knowledge of harmonic frequencies may mean the difference between a happy customer and an unhappy one.

How would you rate the value of this article?

lowest [1](#) [2](#) [3](#) [4](#) [5](#) [6](#) [7](#) [8](#) [9](#) [10](#) highest

Sorry, voting is closed.

Motor Mastery Training

Register for two day Motor Mastery training classes in [Dallas, TX](#) and [Atlanta, GA](#) this December. Choose to attend either one or two days for a complete ECM and induction motor course. Contractors, distributor/OEM reps and instructors all will benefit!

ECM (Electronically Commutated Motors) Training will cover all Fractional Horse Power (FHP) ECM used in OEM residential and light commercial HVAC, Commercial Refrigeration and aftermarket retrofit HVAC.

Induction motor training will cover all Fractional Horse Power (FHP) motors used in residential and light commercial HVAC, Integral Horse Power (IHP) motors used in commercial and industrial applications and capacitors.

Both classes are NATE recognized. All NATE certified technicians will receive a 1 hour credit for each class house toward recertification in all of the forced air disciplines they are currently certified in. For a full class description and registration, please visit [theDealerToolbox.com](#).

3.3 Simplification

As part of our ongoing efforts to simplify the way we serve our distributors we will be taking the following actions for [Century 3.3 inch catalog motors](#).

We are confident these changes will allow us to better serve your 3.3 inch motor needs. Our goal throughout this effort is to work together with you, our valued distributor, to make it easier to do business, and improve our delivery and quality performance.

Features

- Group 1 - DUAL CENTURY & FASCO MODELS: Effective immediately all motors in Group 1 where there is an equivalent Century and FASCO stock motor, production will be transferred over to the FASCO 3.3 inch stock motor. You will be able to purchase the Century brand 3.3 inch motors until the inventory is depleted
- Group 2 - LEGACY 3.3 INCH CENTURY MODELS: All Century stock 3.3 inch motors where a suitable FASCO stock motor does not exist, and the volume warrants, will be redesigned into a new FASCO stock motor. Inventory on these Century 3.3 motors will be available for purchase until the new FASCO catalog motors are in stock.
- Group 3 - OBSOLETE 3.3 INCH CENTURY MODELS: All Century 3.3 inch stock motors that have very low sales volume and do not have a Fasco equivalent will be made obsolete and no longer produced when inventory is depleted.

For information, pricing, or to place an order, contact your Regal Sales Professional or Customer Service today at (800) 672-6495 or visit www.hvac-motors.com

Copyright © 2014 Regal Beloit America, Inc., All rights reserved.
[unsubscribe from this list](#) [update subscription preferences](#)

